

20KM Analog Audio Optical Transceiver



Brief

Extends the transmission range of analog audio by using one fiber optic cable (SM), distance up to 20KM.
Support two bi-directional transmission.

Features

- * RCA analog transmission
- * Distance: max 20KM (SM)
- * Optical connector: SFP (SC)
- * Support mono x2 or stereo x1 audio
- * 2 way bi-directional transmission

Ports Definition



Sender: Inputs x2 / Outputs x2

Bi-directional ↑↓



Receiver: Outputs x2 / Inputs x2



Specifications

	BS-1SA	BS-2SA	BS-2ZA	BS-4SA	BS-4ZA	BS-8ZA
Audio Ways:	1	2	2	4	4	8
Connectors						
Sender:	RCA (red) x1 RCA (white) x1	RCA (red) x2 RCA (white) x2	RCA (red) x2	RCA (red) x4 RCA (white) x4	RCA (red) x4	RCA (red) x8
Receiver:	RCA (red) x1 RCA (white) x1	RCA (red) x2 RCA (white) x2	RCA (white) x2	RCA (red) x4 RCA (white) x4	RCA (white) x4	RCA (white) x8
Bi-directional:	√	√		√		
Extend Distance:	20KM (SM)					
Optical Interface:	GBIC (SC)					
Audio Formate	Mono x1	Mono x2 or Stereo x1	Mono x2 or Stereo x1	Mono x4 or Stereo x2	Mono x4 or Stereo x2	Mono x8 or Stereo x4